



Ublox 8

Navilock NL-8222MP MD6 Serial PPS Multi GNSS Receiver ublox 8 10 m

Description

The MD6 serial multi GNSS Receiver based on u-blox 8 chipset has a built-in antenna for high sensitivity. You can use this GNSS Receiver with a laptop and a suitable routing software for navigation. The MD6 universal connector enables the connection of optional USB or serial connecting cables. The NL-8222MP GNSS receiver is especially designed for installation on a white ground (boat, camper, bus etc.) It is unremarkable and fits into the vehicle concept due to its housing design.



10 m

ltem no. 62530

EAN: 4043619625307

Country of origin: Taiwan, Republic Of China

Package: Retail Box

Specification

- · Connector: MD6 Navilock plug (USB or serial cable are optional available)
- Chipset: u-blox 8 UBX-M8030-KT
- Frequency: GPS: L1, 1575.4200 MHz
 GLONASS: L1, 1602 (k x 0,5625) MHz
 BEIDOU COMPASS: B1, 1561.0980 MHz
 GALILEO: E1, 1575.4200 MHz
 QZSS: L1, 1575.4200 MHz
- · Accepts the signals of up to 72 satellites at the same time
- Supports AssistNow online / offline, SBAS (WAAS, EGNOS, QZSS and MSAS)
- · Supports NMEA 0183 protocols: GGA, GSA, GSV, RMC, VTG
- Auto Baud Rate up to 115200 bps
- PPS signal on pin 6
- Update rate: single GNSS: 18 Hz (e.g. GPS solo) multi GNSS: 10 Hz (e.g. GPS+GLONASS)
- Sensibility max. -167 dBm
- IPX7 protection class
- Operating temperature: -20 °C ~ 60 °C
- Power supply: 5 V DC
- Current consumption: max. 45 mA
- Cold start in ca. 26 seconds
- Hot start in ca. 1 second
- Positioning accuracy: 2.5 m CEP (Circular Error Probable) and 2 m CEP with SBAS
- Cable length: ca. 10 m
- Dimensions (Ø x H without screw thread): ca. 62 mm x 21 mm

Microsoft Sensor and Location Platform (Website)

- Profit from Windows applications (e.g. weather, maps, etc)
- · Supporting the GNSS location platform API (32 bit)

System requirements

- Windows Vista/7/8/8.1/10, Linux Kernel 2.6
- MD6 connection cable

Package content

- MD6 serial receiver
- · Mounting material: stainless steel nut and washer
- · Navilock support CD incl. driver and user manual



Images



